



# Network Remote Keyboard Vectis HX Keyboard

V2.0



Vectis HX Keyboard

Vectis HX Keyboard is a network system controller which controls both analog and network devices. This unique feature is a newly introduced concept into the video surveillance market providing flexibility and scalability for control centers by supporting various components like DVRs and PTZ cameras. And also, its ergonomic and compact design will enhance the usability making operators feel comfortable.

- A new way to control analog and IP devices by supporting both Ethernet and RS485 connection
- Detects all devices in the network automatically and the user can choose what will be added with ease
- Firmware upgrades can be easily done through remote configuration tool – HX INIT – or USB port
- The joystick may be positioned according to individual preferences and is therefore equally well-suited for both left- and right-handed operators
- Fresh look for a long time thanks to its UV-coated body and buttons which is resistant to scratches and fingerprints
- The buttons of Vectis HX Keyboard are organized into 3 distinct groups which make it easier to find the functions you want
- Provides soft buttons making you feel comfortable by requiring only a little pressure
- Speaker and microphone can be directly connected to Vectis HX Keyboard for a two-way voice communication with remote sites
- Frequently used functions can be set as a macro (up to 100) and there are 4 function keys which can be used as a macro shortcut

# Functionalities

## ■ DVR control

Via RS485 or network, Vectis HX Keyboard can control the DVR; i.e. SISTORE AX, Vectis HX series. By plugging an USB mouse into the USB port, you will be able to control specific DVRs directly using the mouse.

## ■ PTZ control

For dome and pan-and-tilt units including SIEMENS CCDA, SCU, BEWATOR SOLARIS dome and etc can be controlled.

## ■ Easy and intuitive setup

Vectis HX INIT software provides a automatic detection of the devices and intuitively easy system configuration. Following languages are supported: GE, EN, FR, IT, SP, NL, PL, PT, CZ, RU (DK, SW, FI and TK in preparation)

## ■ Technical data

|                           |   |
|---------------------------|---|
| Display                   | 2 Line LCD  |
| RS485                     | 2 x Half Duplex (1 x PTZ, 1 x DVR)  |
| Ethernet                  | 10/100 Ethernet   |
| USB                       | 2 x USB 2.0   |
| Audio Input               | 1 line in or Microphone   |
| Audio Output              | 1 line out  |
| Design                    | 2 body (Joystick + Main Control Board), free allocatable Joystick to left and right |
| Firmware Upgrade          | USB or Network  |
| Setup Tool                | LCD setup or Remote setup via Vectis HX INIT  |
| Macro Record/Play         | Up to 100 macros  |
| Function Mapping          | Up to 8 functions   |
| Network DVR Mouse Control | Yes   |
| DVR Menu(General)         | Arrow buttons, Jog/Shuttle  |
| DVR Menu(Display)         | Menu, Display, Group, Freeze, Spot, Sequence, Zoom                                  |
| DVR Menu(Playback)        | Fast Forward/Rewind, Step Forward/Backward, Play, Pause, Clip-copy                  |
| DVR Menu(Emergency)       | Panic, Alarm  |
| PTZ Menu(General)         | Up/Down, Left/Right, Zoom   |
| PTZ Menu(Specific)        | Focus, Iris, Preset, PTZ menu, Alarm reset, Auto panning, Tour, Pattern, Home       |
| Operating Temperature     | 41°F to 104°F (5°C to 40°C)   |
| Operating Humidity        | 0% to 90%   |
| Power Supply              | 5 VDC, 3A   |
| Power Consumption         | Max. 10W  |

## ■ Details for ordering

| Type               | Part no        | Designation        | Weight*       |
|--------------------|----------------|--------------------|---------------|
| Vectis HX Keyboard | S54561-C791-A2 | Vectis HX Keyboard | Approx. 2.1kg |

\* Device incl. packing material, accessories that are included in the delivery, and documentation

Further products and accessories can be found in the Internet: [siemens.com/cctv](https://www.siemens.com/cctv) > Downloads

The information in this document contains general descriptions of technical options available, which do not always have to be present in individual cases. The required features should therefore be specified in each individual case at the time of closing the contract.

© Siemens AG • Document no. A6V10356569 • Edition: **22.03.2012** • Document version: 1.0

Siemens AG  
Siemensallee 84  
D-76187 Karlsruhe  
Tel. +49 721 595 1

[www.siemens.com/securityproducts/int](http://www.siemens.com/securityproducts/int)